

Features

- Up to 20 personal memory slots
- Time, date and day of the week display
- Time and date stamping
- Unread message reminder alert
- Delete all read and unlocked messages
- Protect up to 10 messages
- Battery low indicator
- Out-of-range indicator
- Duplicate message indication
- Continuous message indication
- Memory full indication
- Error message indication
- Back light
- Memory retention
- 1 alarm
- Vibrate/9 pleasing/vibrate then audible/no alert
- Quick browse of first screen messages

Synthesized FLEX™ Numeric Pager



Specifications

Model no.	BRAVO 500
Frequency:	VHF (135 - 175MHz), 280 MHz (278-284MHz)
Code Format:	FLEX, 1600/3200/6400 bps
Channel Spacing:	25 kHz
Frequency Deviation:	+/- 4.8 kHz
Paging Sensitivity:	-104 dBm (c.f. 22.5dB)
EIA Selectivity:	50 dB
EIA Spurious and Image:	50 dB
IM Rejection:	50 dB
Operating Temperature:	-10°C to 50°C
Alert Tone Loudness:	75 dB @ 12 inches
Battery Type:	1 x Alkaline AA
Battery Life:	~70 days (collapse value=4)
Weight (with battery):	45 grams
Dimensions:	55 x 41 x 16 mm

RAD DEV FOR HAZ LOC INT SAFE
CI.I,Div1,Gr.ABCD;CI.II,Div2,Gr.FG

