

Features

- 2-line alphanumeric display, 18 characters per line
- Up to 30 personal message slots and 15 maildrops
- Up to 16 notebook slots
- Time, date and day of the week display
- Time, day and date stamping
- Unread message reminder alert
- Delete all read and unlocked messages
- Battery low indicator
- Battery life indicator
- Out-of-range indicator
- Continuous message indication
- Error message indication
- Back light
- Memory retention
- 2 alarms
- Vibrate/5 pleasing/2 user programmable/vibrate then audible/no alert
- 3 speed scrolling of message
- Screen contrast (0-7 level)
- Maildrop alert - individual slot control

Synthesized FLEX™ 2-line Alphanumeric Pager



Specifications

Model no.	BRAVO 600	
Frequency:	VHF (135 - 175MHz), 280MHz (278-284MHz) 900MHz (929-923MHz)	
Code Format:	FLEX, 1600/3200/6400 bps	
Channel Spacing:	25 kHz	
Frequency Deviation:	+/- 4.8 kHz	
Paging Sensitivity:	-104 dBm (c.f. 22.5dB)	
	VHF/280MHz	900MHz
EIA Selectivity:	50 dB	40 dB
EIA Spurious and Image:	50 dB	40 dB
IM Rejection:	50 dB	40 dB
Operating Temperature:	-10°C to 50°C	
Alert Tone Loudness:	75 dB @ 12 inches	
Battery Type:	1 x Alkaline AA	
Battery Life:	~70 days (collapse value=4)	
Weight (with battery):	45 grams	
Dimensions:	57 x 41 x 17.5 mm	

RAD DEV FOR HAZ LOC INT SAFE
Cl.I,Div1,Gr.ABCD;Cl.II,Div2,Gr.FG

